



Reproduced By GLOBAL
ENGINEERING DOCUMENTS
With The Permission of EIA
Under Royalty Agreement

CB14

EIA ENGINEERING BULLETIN

Contact Lubrication

CB14

JUNE 1993

ELECTRONIC INDUSTRIES ASSOCIATION
ENGINEERING DEPARTMENT



NOTICE

EIA Engineering Standards and Publications are designed to serve the public interest through eliminating misunderstandings between manufacturers and purchasers, facilitating interchangeability and improvement of products, and assisting the purchaser in selecting and obtaining with minimum delay the proper product for his particular need. Existence of such Standards and Publications shall not in any respect preclude any member or nonmember of EIA from manufacturing or selling products not conforming to such Standards and Publications, nor shall the existence of such Standards and Publications preclude their voluntary use by those other than EIA members, whether the standard is to be used either domestically or internationally.

Recommended Standards and Publications are adopted by EIA in accordance with the American National Standards Institute (ANSI) patent policy. By such action, EIA does not assume any liability to any patent owner, nor does it assume any obligation whatever to parties adopting the Recommended Standard or Publication.

Technical Bulletins are distinguished from EIA Recommended Standards or Interim Standards, in that they contain a compilation of engineering data or information useful to the technical community, and represent approaches to good engineering practices that are suggested by the formulating committee.

This Bulletin is not intended to preclude or discourage other approaches that similarly represent good engineering practice, or that may be acceptable to, or have been accepted by, appropriate bodies. Parties who wish to bring other approaches to the attention of the formulating committee to be considered for inclusion in future revisions of this Bulletin are encouraged to do so. It is the intention of the formulating committee to revise and update this Bulletin from time to time as may be occasioned by changes in technology, industry practice, or government regulations, or for other appropriate reasons.

(Formulated under the cognizance of the EIA CE-2.0 Committee on National Connector Standards.)

Published by

• ELECTRONIC INDUSTRIES ASSOCIATION 1993

Engineering Department
2001 Pennsylvania Ave., N.W.
Washington, D.C. 20006

PRICE: Please refer to the current

Catalog of EIA & JEDEC STANDARDS & ENGINEERING PUBLICATIONS
or call Global Engineering Documents, USA and Canada (1-800-854-7179)
International (303-792-2181)

All Rights Reserved
Printed in U.S.A.

PLEASE!
DON'T VIOLATE
THE
LAW!

This document is copyrighted by the EIA and may not be reproduced without permission.

Organizations may obtain permission to reproduce a limited number of copies through entering into a license agreement with the EIA. For information, contact:

**EIA Engineering Publications Office
2001 Pennsylvania Ave., N.W.
Washington, D.C. 20006
(202)457-4963**

CONTACT LUBRICATION

PURPOSE AND SCOPE

The purpose of this document is to review contact lubricants used in signal contact systems for electronics. Factors affecting the use of lubricants will be discussed including those area's requiring further study. Applicable advantages, limitation and cautions are indicated. A bibliography is included if further investigation is desired.

It is not the intent of this document to make a conclusion or forward a recommendation.

Due to the wide variation of available lubricants (both generic and proprietary), the specific situations briefly discussed herein may not be of issue contingent on the lubricant formulation which may have been designed to resolve a specific problem.

In considering the use of a lubricant, the reader is advised to assess the specific areas of interest and chose a lubricant which best fits the application after proper evaluation techniques have been performed.

A. BIBLIOGRAPHY

The information contained herein has been based from various publications and papers as indicated in the bibliography contained at the end of this document. For more specific information, these publications should be researched as applicable.

B. BASIC PHENOMENON

Two surfaces in contact with each other appear to form a relatively large continuous contact area. In reality the real area of contact is formed by contact asperities (commonly called "a-spots"). These asperities are actually metallic peaks in contact with each other and represent as low as 1% of the apparent contact area.

When a contact force is applied these peaks contact each other and may actually enlarge dependent on the magnitude of the applied force. This may result in localized cold welding and/or potential galling.

Cold welding is defined as the solid state bonding between atoms of the metallic surface areas in contact. Contamination free surfaces are required for this to fully occur. The presence of contaminants on the surface can minimize cold welding.

Galling is defined as a wear condition resulting from friction between the asperities of the contacting surfaces. This can result in localized welding and subsequent metal surface disruption, metal transfer and/or further roughening of the mating surfaces.

In addition, when one of the two, or both contacting surfaces are moved relative to each other, any localized cold welding between the asperities has to be broken or sheared. This shearing force is a function of a number of variables such as compressive forces, surface conditions, cleanliness etc.

BASIC PHENOMENON - Continued

When a lubricant is applied to a surface, the fluid generally forms small droplets. When surfaces are brought into contact, these droplets are spread over the entire surfaces in the form of a thin film. The film is thin enough to be penetrated in several areas by the material asperities thus not affecting electrical resistance. The impact of this film results in minimizing cold welding, reduces shear forces involved and hence reduces wear, galling and frictional forces.

C. CONNECTOR ATTRIBUTES AFFECTED BY LUBRICATION

1. WEAR: The term "wear" indicates the "forced" removal of contact material during the sliding action which occurs. This removal may be a result of the transfer phenomena, loss of loose particles (debris), pushing material aside, etc. The following are the basic wear mechanisms which exist.
 - a) ABRASIVE: Wear resulting from rough, sharp hard materials or a combination thereof in contact with a softer material. An example of this is a lead-in chamfer of a mating pcb against a gold or tin (ally) plating of the mating contact. Lubricants may not be effective in these situations.
 - b) BRITTLE FRACTURE: This is the cracking of a plated surface perpendicular to the direction of sliding. This type of wear can occur on low strength materials or a poorly controlled plating process. Lubrication by itself will not prevent this type of wear from occurring.

CONNECTOR ATTRIBUTES AFFECTED BY LUBRICATION - Continued

- c) ADHESIVE: This is the most common type of wear common to connectors. Basically this type of wear results from cold welding and/or the transfer phenomena. This type of wear is significantly reduced when a lubricant is used on the surfaces.

The rate of wear sharply increases from "mild" to "severe" usually when a specific load is achieved. Use of a lubricant will result in this transition to occur at higher force levels with all other factors being equal.

Lubrication will also allow thinner gold plating to be used due to the reduction of the wear rate.

2. CORROSION: A lubricant can "seal" off reactive surfaces from the surrounding atmosphere. It can also significantly reduce pore corrosion as well. Microcrystalline wax or a mixture of wax and an oil are effective in this case.

Fretting corrosion may be inhibited by the use of a fluid lubricant. It will reduce fretting wear on of gold platings as well as inhibiting frictional polymers in palladium (alloy) systems.

3. LOWER MATING FORCES: A lubricant by its inherent nature reduces coefficient of friction and this decreases the mating force of a connector system. This can be an important feature for high density connector currently evolving. Said reduction may be as great as 80% contingent on contact configuration (entry geometry), surface, conditions (eg. roughness, cleanliness, etc.). This reduction may be achieved without reducing normal force and may allow an actual increase in this attribute without adversely affecting the resultant mating force.

CONNECTOR ATTRIBUTES AFFECTED BY LUBRICATION - Continued

Typical coefficient of frictions are as follows:

Clean surfaces : 0.3 to 1.0

Lubricated Surfaces : 0.15 to 0.2

There are two basic equations which may be used in understanding frictional forces:

a) $F = (KN/H)S$ F = Frictional Force
 K = Constant, Proportionality
 N = Normal Force
 H = Hardness of the soft material
 S = Shear Strength of the soft material

b) $F = \mu N$ F = Frictional Force
 μ = Coefficient of Friction
 N = Normal Force

In essence, frictional forces is a function of cold welding. Cold Welding is a function of the adhesive bonding of metals in contact relative to the "real" area contact and the shearing force required. A lubricant will minimize the "real" area of contact. It also exhibits a much lower shear force and as a result of these factors, the frictional forces are reduced.

D. CONDITIONS TO BE EVALUATED

1. COSTS: The addition of a lubricant is an additional step in the manufacturing process and as a result represents additional costs. This cost can greatly vary contingent on the technique.

CONDITIONS TO BE EVALUATED - Continued

2. CLEANING: If a lubricant is applied by the connector manufacturer, cleaning will remove the lubricant and, hence, no advantage will be gained.
3. PARTICULATE RETENTION: A lubricate can increase the retention of particulates from the environment. This can be in the form of dust and/or fibers. Recent studies have indicated that dust does not adversely affect the function of a lubricant. Further study is required relative to fibers.
4. CONTAMINATION OF ADJACENT SURFACES: Certain lubricants and the volatile carriers can transfer to adjacent surfaces. Non-spreading, low volatility lubricants are, however, unlikely to transfer.
5. A lubricant reduces mating forces. It will also reduce unmating forces. Thus, to prevent "walk out", connectors with a lubricant should be "locked" together by jackscrews or other hardware locking techniques used in its application.
6. Fluid lubricants contingent on their formulation may evaporate. The rate of evaporation varies and is temperature dependent. Lubricants used in applications beyond 65°C should be researched prior to using.

E. COMMON CONTACT LUBRICANTS

The following are typical contact lubricants available:

- a) Polyphenylethers : 5-PPE and 6-PPE
- b) Hydrocarbon oils : Mineral Oils
- c) Perfluoroalkylpolyethers
- d) Polyolefin

For additional information relative to generic or proprietary contact lubricants, the following companies may be contacted:

Monsanto, St. Louis, MO
William F. Nye, New Bedford, MA
Dow Chemical Corporation, Midland, MI
Tenneco Chemicals, Piscataway, NJ
Rohm & Haas, Philadelphia, PA
Electrotube Corporation, Syosset, NY

BIBLIOGRAPHY

The following is not a complete listing of all reference work published in the area of contact lubrication. It does list key references. Additional references are contained with the publications listed.

1. S.J. Krumbein, Mort Antler, "Inhibition of Corrosion and Wear on Gold Plated Contacts", NEP/CON, 1967.
2. L.P. Solos, "Fundamental Study of Gold Plating and Dry Film Lubricant System for Long Life Sliding Contacts", Nat. Aerospace Electronics Conf., NAECON, 1964.
3. G. Steinberg, S.W. Chaikin, "Lubrication of Electrical Contacts with Solid Thin Films of Organic Compounds", Holm Conf., 1966.
4. M. Antler, "The Lubrication of Gold", Wear, 1963.
5. R.V. Chiarenzelli, B.C. Henry, "Lubricating Separable Electric Contacts and Tarnish Prevention", Lubrication Eng., 1966.
6. R. Geckle, L. Witt, "Graphite as a Sliding Lubricant" Plating, 1972
7. W. Abbott, J.H. Whitley, "The Lubrication and Environmental Protection of Alternatives to Gold for Electronic Connectors", Holm Conf., 1975.
8. F.D. Messina, "Evaluation of Microcrystalline Wax Dispersion Lubricants", Holm Conf., 1980.
9. "Lubricants for Electrical Contacts", ECR-08E, Elektronik-Centralen, 1971.
10. P. Villien, "Effect of Lubrication on Environmental Reliability of Gold Plated Connectors", SPM-81, Elektronik-Centralen, 1985.
11. M. Antler, "Sliding Wear of Metallic Contacts", IEEE Trans. 1981.
12. M. Antler, "Electronic Connector Contact Lubricants: The Polyether Fluids", Holm Conf., 1986.

BIBLIOGRAPHY - Continued

13. M. Antler, M.Feder, "Wear and Friction of Electrodeposited Palladium Contacts: Thin Film Lubrication with Fluids and with Gold", Elec. Comp. Conf., 1986.
14. C.A.Hague, M.D. Richardson, E.T. Ratliff, "Effect of Dust on Contact Resistance of Lubricated Connector Contact Materials", Holm Conf., 1985.
15. W.O. Freitag, "Lubricants for Separable Connectors", Holm Conf., 1976.
16. R.V. Steenstrup, V.M. Fiacco, L.K. Schultz, "A Comparative Study of Inhibited Lubricants for Dry Circuits Sliding Contacts", IEEE Trans, 1983.
17. M. Antler, "Sliding Studies of New Connector Contact Lubricants".
18. Tech. Staff Airborn, "Surface Conditioning Study", Tech Bulletin No. 100, 1988.

